

25KW¹ STANDBY GENERATOR

Engine Brand Briggs & Stratton

CC 1587

Number of Cylinders 4

Operation Fully Automatic

Voltage (V) 120/240

Running Amps 104 Liquid Propane 104 Natural Gas

Alternator Type Brushed

Fuel Consumption (Cubic Feet per Hour @ 1/2 Load) 105 ft³ / 2.9 gal/hr (Liquid Propane) 252 ft³/hr (Natural Gas)

Fuel Consumption (Cubic Feet per Hour @ Full Load) 155 ft³ / 4.3 gal/hr (Liquid Propane) 368 ft³/hr (Natural Gas)

Weekly Exerciser Yes

25KW¹ STANDBY GENERATOR

Battery/Battery Charger	Included
--------------------------------	----------

Overcrank Protection	Yes
-----------------------------	-----

Hour Meter	Yes
-------------------	-----

Diagnostic Alerts with Remote System Status	Low Oil Shutdown, Engine Does Not Start, Low Frequency, Engine Overspeed, Low Voltage, Low Battery Voltage, Engine Temp High, Transfer Switch Fault, Over Voltage Protection
--	--

Length (in)	71
--------------------	----

Width (in)	32.3
-------------------	------

Height (in)	37
--------------------	----

Weight (lbs)	1056
---------------------	------

Warranty (Product)	4 Year Limited Parts, Labor and Travel
---------------------------	--

*NG = Natural Gas; LP = Liquid Propane. **Fuel consumption rates are estimated based on normal operating conditions at 1/2 load. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances - fuel flow rates may vary depending on these factors.